



Sanyo Denki - PY Super BL Servo Amplifiers

PY0A050A



In Stock, Ships in 3-5 Days

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY0A050A** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Absolute Position Output Signal:	9600 bps (asynchronous) / 0.5 Mbps (Manchester)	Built-in Dynamic Brake:	Yes (emergency braking)	Control Circuit Input Power:	1? 200-230VAC +10%/-15%, 50/60Hz ±3Hz
Control Function:	Velocity, torque or position control	Main Circuit Input Power:	3? 200-230VAC +10%/-15%, 50/60Hz ±3Hz	Mass:	2.7 kg
Operating Ambient Temperature:	0°C to 55°C (32°F to 131°F)	Operating/Storage Humidity:	?90% RH (no condensation)	Protection Functions (Electrical):	Overcurrent, overload, overtemp, overspeed, low voltage
Protection Functions (System):	Sensor error, CPU error	Regenerative Processing:	Built-in regen circuit; resistor optional	Storage Temperature:	?20°C to +65°C (?4°F to +149°F)
Velocity Control Range:	1:5000	Vibration Resistance:	0.5G @10-55Hz (XYZ), 2h	Last Verified:	08/22/2025 7:22 AM

Contact Us

📍 1620 Old Apex Road, Cary, NC 27513, USA

📞 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

🌐 International: [1-919-443-0207](tel:1-919-443-0207)

📠 Fax: [1-919-867-6204](tel:1-919-867-6204)

✉ Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.