

Sanyo Denki - PY Super BL Servo Amplifiers

PY0A050A1G31P01



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY0A050A1G31P01** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Control Function:	Velocity, torque, or position control 1? 200-230 VAC +10%/-15%, 50/60 Hz ±3 Hz	Humidity:	90% RH, non-condensing 3? 200-230 VAC +10%/-15%, 50/60 Hz ±3 Hz	Induced Voltage Constant:	46.0 V/krpm
Input Power (Control):	0 to 55°C	Input Power (Main):	0.50 ?	Maximum Speed:	2000 rpm
Operating Temperature:	-20 to 65°C	Phase Resistance:	1.32 N·m/Arms	Rated Torque:	9.3 N·m
Storage Temperature:	08/22/2025 9:06 PM	Torque Constant:		Weight:	23.1 kg
Last Verified:					

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.