



Sanyo Denki - PY Super BL Servo Amplifiers

PY0A050A1G3MP01



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY0A050A1G3MP01** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Communication Interface:	RS-485 / Modbus RTU	Control Method:	Vector Control / Torque Control	Cooling Method:	Fan Cooling
Dimensions (L x W x H):	250 mm x 180 mm x 100 mm	Efficiency:	? 95%	Frequency:	50/60Hz
Input Voltage:	1 PHASE 200-230V AC	Low Input Current:	0.2 AMPS	Max Output Current:	15 A
Maximum Input Current:	13.3 AMPS	Operating Temperature Range:	-10°C to +50°C	Output Voltage:	3 PHASE 0-326V
Pulse Width Modulation (pwm):	20.8kHz	Rated Output Power:	5 kW	Short-Circuit Protection:	Yes (Integrated circuit protection)
Last Verified:	06/01/2025 10:19 PM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.