



Sanyo Denki - PY Super BL Servo Amplifiers

PY0A050H0P26P00



In Stock, Ships in 3-5 Days

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY0A050H0P26P00** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Continuous Stall Armature Current: 31.6 Arms

Induced Voltage Constant (ke?): 36.7 V/krpm

Maximum Revolution Speed: 2500 rpm

Rated Armature Current: 24.1 Arms

Rated Torque: 21.5 N·m
07/06/2025

Last Verified: 10:34 AM

Continuous Stall Torque: 32.0 N·m

Instantaneous Maximum Stall Armature Current: 79.7 Arms

Mechanical Time Constant: 0.68 msec

Rated Output: 4500 W
Torque Constant (kt): 1.05 N·m/Arms

Electrical Time Constant: 33 msec

Instantaneous Maximum Stall Torque: 70.0 N·m

Phase Armature Resistance: 0.043 ?

Rated Revolution Speed: 2000 rpm
Weight: 22.0 kg

Contact Us

📍 1620 Old Apex Road, Cary, NC 27513, USA

📞 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

🌐 International: [1-919-443-0207](tel:1-919-443-0207)

📠 Fax: [1-919-867-6204](tel:1-919-867-6204)

✉ Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.