

Sanyo Denki - PY Super BL Servo Amplifiers**PY0A100J0C77B00** **In Stock, Ships in 3-5 Days**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer

Secure Online
CheckoutFree Ground
ShippingOne Year
Warranty

The **PY0A100J0C77B00** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Communication Interface:	RS-485 and CANopen compatible	Control Mode:	Vector control (torque control)	Cooling Method:	Forced air cooling
Dynamic Brake Delay Time:	24ms	Efficiency:	Greater than 95%	Input Signal Type:	Analog and Pulse/DIR inputs
Mounting:	DIN rail mounting	Operating Temperature:	-10 °C to +55 °C	Overload Capacity:	150% for 60 seconds
Protection Features:	Over-voltage, over-current, and over-temperature protection	Rated Current:	100 A	Rated Output Power:	Approximately 10 kW
Rated Voltage:	200 VAC	Switching Frequency:	Approximately 400 Hz PWM	Weight:	Approximately 15 kg
Last Verified:	07/05/2025 7:49 PM				

Contact Us 1620 Old Apex Road, Cary, NC 27513, USA Toll Free: [1-888-551-3082](tel:1-888-551-3082) International: [1-919-443-0207](tel:1-919-443-0207) Fax: [1-919-867-6204](tel:1-919-867-6204) Email: sales@automation-factory.com**Shipping Options****Payment Methods**

Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.