

Sanyo Denki - PY Super BL Servo Amplifiers

PY0A150A0R62S03



In Stock, Ships in 3-5 Days

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY0A150A0R62S03** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Control Bus Capacity: 40 VA, 0.2 A
Cooling Fin Dimensions: Height >197 mm, Width 142 mm
Drive Type: AC Drive
Phase: 3-phase
Standards Compliance: Meets industrial standards
Last Verified: 07/06/2025 2:31 AM

Control Interface:

Cooling Method:

Installation:

Power Bus Capacity:

Total Power Dissipation:

Standard control signals

Air cooled

Panel mount design

8.3 kVA, 24.0 A

260W (150W PCB, 110W heatsink)

Cooling Fin Cut-out Width:

Current Rating:

Mounting Cut-out Height:

Protection Features:

Voltage Rating:

75 mm


150A

225 mm

Built-in safeguards typical for servo amplifiers

Approximately 200-230 VAC

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

