

## Sanyo Denki - PY Super BL Servo Amplifiers

### PY2A015A0M31P00



 **In Stock, Ships Fast**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online  
Checkout



Free Ground  
Shipping



One Year  
Warranty

The **PY2A015A0M31P00** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

## Specifications

<b>Altitude Rating:</b>	Up to 1000 m above sea level	<b>Control Circuit Input Power:</b>	Single-phase, 200-230 VAC (+10%/-15%), 50/60 Hz $\pm$ 3 Hz	<b>Control Function:</b>	Velocity, torque, or position control via parameters
<b>Control Modes:</b>	Position, Speed, Torque	<b>Cooling Fan Lifetime:</b>	Approx. 5 years at 40°C ambient	<b>Environmental Compliance:</b>	Meets IEC 664-1/2.5.1 Pollution Level 2
<b>LED Display:</b>	7-segment LED for status and alarm codes	<b>Main Circuit Input Power:</b>	3-phase, 200-230 VAC (+10%/-15%), 50/60 Hz $\pm$ 3 Hz	<b>Mass:</b>	Approx. 1.5 kg
<b>Operating Ambient Temperature:</b>	0°C to 55°C	<b>Operating Humidity:</b>	Up to 90% RH (no condensation)	<b>Power Supply:</b>	Built-in tray-type power supply
<b>Protection Functions:</b>	Overcurrent, overload, overheat & sensor-error protection	<b>Storage Temperature:</b>	-20°C to 65°C	<b>Vibration Resistance:</b>	0.5G, 10 <sup>5</sup> Hz, 2 h in X/Y/Z directions
<b>Last Verified:</b>	07/06/2025 5:22 AM				

## Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: [sales@automation-factory.com](mailto:sales@automation-factory.com)

## Shipping Options



## Payment Methods

