
# Click to Request a Quote!

sales@automation-factory.com 1-919-443-0207

#### Sanyo Denki - PY Super BL Servo Amplifiers

# PY2A015A0M61S00





- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- Up to half the cost of the manufacturer





Secure Online Checkout

Free Ground Shipping

One Year Warranty

100-115 V/200-

230 V AC

50/60 Hz

(PY2A015)

overheat,

overspeed,

Overcurrent, overload.

±10%/-15%,

Approx. 1.5 kg

The PY2A015A0M61S00 is a part of the PY Super BL Servo Amplifiers Series by Sanyo Denki.

### **Specifications**

Control modes:

Velocity, torque,

or position via

parameter switch

200-230 V AC

±10%/-15%,

Input power (3?): 50/60 Hz **Humidity:** 

**LED display:** 

0°C to 55°C

Operating temperature:

**Power supply** structure:

Built-in resistor; optional external

Regeneration: connection

0.5 G, 10 ₹ 55 Hz,

**Vibration endurance:** 2 h (XYZ axes)

Shock resistance:

Last Verified:

Built-in tray-type

supply

?90% RH, non-

Internal status

condensing

and alarm

indicator

Up to 2 G

08/22/2025

5:57 AM

Protection functions: sensor error

Input power (1?):

Mass:

-20°C to 65°C

Storage temperature:

#### **Contact Us**

1620 Old Apex Road, Cary, NC 27513, USA

Toll Free: 1-888-551-3082

International: 1-919-443-0207

Fax: <u>1-919-867-6204</u>

Email: sales@automation-factory.com

# **Shipping Options**









# **Payment Methods**









Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.