



Sanyo Denki - PY Super BL Servo Amplifiers

PY2A015A1M61P00



In Stock, Ships Fast

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY2A015A1M61P00** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Alarm Code Output:	4-bit binary coded	Control Modes:	Velocity, torque, position control (parameter switching)	Current Limit Input:	Yes
Encoder Clear Input:	Yes	Humidity (op/storage):	?90% RH, no condensation	Input Power (3-phase):	200 ^{SPR} 230 VAC ±10%/ ^{SPR} 15%, 50/60 Hz ±3 Hz
Input Power (single-phase):	200 ^{SPR} 230 VAC; optional 100 VAC	Operating Ambient Temperature:	0°C to 55°C	Proportional Control Input:	Analog voltage
Storage Temperature:	-20°C to 65°C	Last Verified:	07/05/2025 10:39 AM		

Contact Us

1620 Old Apex Road, Cary, NC 27513, USA

Toll Free: [1-888-551-3082](tel:1-888-551-3082)

International: [1-919-443-0207](tel:1-919-443-0207)

Fax: [1-919-867-6204](tel:1-919-867-6204)

Email: sales@automation-factory.com

Shipping Options



Payment Methods

