

Sanyo Denki - PY Super BL Servo Amplifiers

PY2A015A3-AL



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY2A015A3-AL** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Ac Voltage:	200V	Command Voltage (MO):	±2.0 VDC at 100 min? ¹ forward rotation	Efficiency:	IE 2
Frequency:	3000r/min	Input Current:	0.2 A/3.4 A	Input Impedance:	Approximately 10k?
Input Voltage:	AC 200 V	Phase:	Three-phase	Position Output Signals:	1 Mbps or higher (with absolute encoder)
Power:	200W	Protect Feature:	Waterproof	Pulse Output Signal:	1 MHz Max. input pulse frequency
Type:	Servo motor	Velocity Monitor (VMO):	0.5 V/120 V at 100 min? ¹	Voltage Variation Tolerance:	±10.1% (170V to 253V)
Last Verified:	07/05/2025 8:27 PM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.