

Sanyo Denki - PY Super BL Servo Amplifiers

PY2A015A3



♣ In Stock, Ships in 3-5 Days

- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- ☑ Up to half the cost of the manufacturer



Free Ground Shipping

One Year Warranty

The **PY2A015A3** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Continuous Stall Armature Current:	8.0 Arms	Continuous Stall Torque: Instantaneous
Induced Voltage Constant:	18.6 V/krpm	Maximum Stall Armature Current:
Maximum Revolution Speed:	4500 rpm	Mechanical Time Constant:
Rated Armature Current:	6.9 Arms	Rated Output:
Rated Torque:	3.19 Nxm (32.5 kgxcm) 05/08/2025	Torque Constant:
Last Verified:	9:48 AM	

3.92 Nxm (40 kgxcm)	Electrical Time Constant:	11 msec
23.2 Arms	Instantaneous Maximum Stall Torque:	10.3 Nxm (105 kgxcm)
0.80 msec	Phase Armature Resistance:	0.51 ?
1000 W	Rated Revolution Speed:	3000 rpm
0.53 Nxm/Arms	Weight (including Wiring):	5.4 kg

Contact Us

- ♀ 1620 Old Apex Road, Cary, NC 27513, USA
- J Toll Free: <u>1-888-551-3082</u>
- International: <u>1-919-443-0207</u>
- <u> Fax: 1-919-867-6204</u>
- Email: <u>sales@automation-factory.com</u>

Shipping Options



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.