

## Sanyo Denki - PY Super BL Servo Amplifiers

PY2A015E0XXYPH1



Request a Quote

- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- ☑ Up to half the cost of the manufacturer



4.90 N?m

Free Ground Shipping

One Year Warranty

The PY2A015E0XXYPH1 is a part of the PY Super BL Servo Amplifiers Series by Sanyo Denki.

## **Specifications**

Continuous Stall Armature Current:	8.1 Arms
Induced Voltage Constant:	22.6 mV/min-1
Maximum Revolution Speed:	4500 min-1
Rated Output:	1500 W
Torque Constant:	0.65 N?m/Arms
Last Verified:	06/01/2025 2:28 PM

Iorque:	
Instantaneous Maximum Stall	26.5 Arms
Armature Current:	
Phase Armature Resistance:	0.42 ?
Rated Revolution Speed:	3000 min-1
Weight (including Abs- e):	6.6 kg

**Continuous Stall** 

Electrical Time Constant:	13 msec
Instantaneous Maximum Stall Torque:	14.7 N?m
Rated Armature Current:	8.4 Arms
Rated Torque:	4.79 N?m
Weight (including Ab rii):	<b>5-</b> 6.6 kg

## Contact Us

- 1620 Old Apex Road, Cary, NC 27513, USA
- Toll Free: 1-888-551-3082
- International: <u>1-919-443-0207</u>
- Fax: 1-919-867-6204
- Email: sales@automation-factory.com

## **Shipping Options**



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.