

Sanyo Denki - PY Super BL Servo Amplifiers

PY2A015H0M86Z01



 **In Stock, Ships Fast**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY2A015H0M86Z01** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Built-in regenerative resistor:	Optional	Control circuit input voltage:	100 ^{SPR} 115 VAC or 200 ^{SPR} 230 VAC (+10%/ ^{SPR} 15%, 50/60 Hz)	Control function:	Velocity, torque or position control
Display indicator:	7-segment LED for status/alarms	Main input voltage (3-phase):	200 ^{SPR} 230 VAC (+10%/ ^{SPR} 15%, 50/60 Hz)	Main input voltage (single-phase):	100 ^{SPR} 115 VAC (+10%/ ^{SPR} 15%, 50/60 Hz)
Mass:	~1.5 kg	Operating temperature:	0°C to 55°C	Operating/storage humidity:	Up to 90% RH (no condensation)
Power supply design:	Integrated tray-type power supply	Protection features:	Overcurrent, overload, overheating protection	Shock resistance:	Up to 2 G
Storage temperature:	-20°C to 65°C	Vibration resistance:	0.5 G, 10 ^{SPR} 55 Hz, 2 hr (XYZ axes)	Last Verified:	08/22/2025 8:23 AM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

