

Sanyo Denki - PY Super BL Servo Amplifiers

PY2A030E0XXXPT0



 **In Stock, Ships Fast**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY2A030E0XXXPT0** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Charge/Power indicator:	yes	Electrical Time Constant:	5.3 msec	Enclosure Type:	Metal casing (EMI-shielded)
Induced Voltage Constant:	47.0 mV/min?1	Input 1 phase current:	0.2 A	input 3 phase current:	5.8 A
Input 3-Phase Voltage:	230V	Instantaneous Maximum Stall Armature Current:	17.9 Arms	Mechanical Time Constant:	4.9 msec
Mounting:	Din Rail Or Base mounting	Output 3 phase current:	5.2 A	Phase Armature Resistance:	0.84 ?
PWM Frequency:	20.0 Hz	Torque Constant:	1.34 N?m/Arms	Weight With Abs-rii:	16.2 kg
Last Verified:	08/22/2025 4:17 PM				

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.