



Sanyo Denki - PY Super BL Servo Amplifiers

PY2A030E0XXYPH2



In Stock, Ships Fast

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY2A030E0XXYPH2** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Command Input Voltage: ±2.0 VDC

Control Circuit Power:

1-? 200-230 VAC
(+10%/SPR15%),
50/60 Hz ±3 Hz

Control Functions:

Velocity, torque,
position

Display: Internal status & alarms

Dynamic Brake:

Built-in

Main Circuit Power:

3-? 200-230 VAC
(+10%/SPR15%),
50/60 Hz ±3 Hz

Operating Ambient Temperature: 0 to 55 °C (32 to 131 °F)

Protection Functions:
Velocity Monitor
Output Voltage:

Overcurrent,
overload,
overspeed, sensor
error, regen error
2.0 V ±10%
@1000 min?¹

Regenerative Processing:

Built-in

Storage Temperature: SPR20 to 65 °C
(SPR4 to 149 °F)

Weight:

approx. 4.4 kg

Last Verified: 08/21/2025 8:04 PM

Contact Us

1620 Old Apex Road, Cary, NC 27513, USA

Toll Free: [1-888-551-3082](tel:1-888-551-3082)

International: [1-919-443-0207](tel:1-919-443-0207)

Fax: [1-919-867-6204](tel:1-919-867-6204)

Email: sales@automation-factory.com

Shipping Options



Payment Methods

