

Sanyo Denki - PY Super BL Servo Amplifiers

PY2A050E4XXXPT0



 **In Stock, Ships Fast**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY2A050E4XXXPT0** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Communication Interface:	RS-485 / CAN (or similar industrial bus)	Control Mode:	Analog/Digital control	Cooling Method:	Fan cooled
Efficiency:	Up to 95% under rated conditions	Operating Temperature:	Typically $\pm 10^{\circ}\text{C}$ to 50°C	Output Current:	Approximately 50 A
Physical Dimensions:	Approx. 200 x 150 x 80 mm (may vary with configuration)	Power Supply:	110/220 V AC (standard)	Protection Features:	Overcurrent, overvoltage, and overtemperature protection
Switching Frequency:	Approximately 4 kHz	Weight:	Approximately 8 kg	Last Verified:	07/06/2025 12:08 AM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.