



Sanyo Denki - PY Super BL Servo Amplifiers

PY2C015U0XXXC08



In Stock, Ships in 3-5 Days

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY2C015U0XXXC08** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Applicable Load Inertia:	$2.04 \times 10^{-4} \text{ kg} \cdot \text{m}^2 \text{ (GD}^2/4\text{)}$	Continuous Stall Armature Current:	6.3 Arms	Continuous Stall Torque:	4.90 N·m
Holding Brake Exciting Voltage:	24/90 V (DC) $\pm 10\%$	Holding Brake Inertia:	$0.40 \times 10^{-4} \text{ kg} \cdot \text{m}^2 \text{ (GD}^2/4\text{)}$	Holding Brake Torque:	7.84 N·m or more
Induced Voltage Constant:	29.0 mV/rpm	Instantaneous Maximum Stall Torque:	17.7 N·m	Maximum Revolution Speed:	3000 rpm
Phase Armature Resistance:	0.67 Ω	Rated Armature Current:	6.5 Arms	Rated Output:	1500W
Rated Torque:	4.79 N·m	Torque Constant:	0.83 N·m/Arms	Weight With Abs-e:	6.4 kg
Last Verified:	08/22/2025 6:20 PM				

Contact Us

📍 1620 Old Apex Road, Cary, NC 27513, USA

📞 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

🌐 International: [1-919-443-0207](tel:1-919-443-0207)

📠 Fax: [1-919-867-6204](tel:1-919-867-6204)

✉ Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.