

Sanyo Denki - PY Super BL Servo Amplifiers

PY2C030U0XXXC06



 **In Stock, Shipping Varies**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY2C030U0XXXC06** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Control Function:	Velocity, torque or position control	Dynamic Brake:	Built-in	Input Power:	Single-phase 200-230 VAC, 50/60 Hz
LED Display:	Internal status and alarm indication	Mass:	2.0 kg	Max Input Pulse Frequency:	2M pulses/sec
Operating Humidity:	Up to 90% RH (no condensation)	Operating Temperature:	0 to 55°C	Position Signal Output:	9600 bps (start-stop) or 1 Mbps (Manchester)
Protections:	Overcurrent, overload and phase-loss	Regenerative Processing:	Built-in circuit (external resistor optional)	Storage Temperature:	-20 to 65°C
Vibration Resistance:	0.5 G at 10-55 Hz	Last Verified:	08/21/2025 10:59 PM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.