

Sanyo Denki - PY Super BL Servo Amplifiers

PY9A300U0XXXC01



 **Request a Quote**

- ✓ Get a Quote in 5 minutes
- ✓ Parts ship in as little as 24 hours
- ✓ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **PY9A300U0XXXC01** is a part of the **PY Super BL Servo Amplifiers Series** by **Sanyo Denki**.

Specifications

Continuous Stall Armature Current:	31.6 Arms	Continuous Stall Torque:	32.0 N·m (326 kg·cm)	Electrical Time Constant:	33 msec
Induced Voltage Constant:	36.7 V/krpm (or 36.7 mV/min? ¹)	Inertia:	58.1×10 ^{??} kg·m ² (59.1 g·cm·s ²)	Instantaneous Maximum Stall Armature Current:	79.7 Arms
Instantaneous Maximum Stall Torque:	70.0 N·m (714 kg·cm)	Maximum Revolution Speed:	2500 rpm	Mechanical Time Constant:	0.68 msec
Phase Armature Resistance:	0.043 ?	Rated Armature Current:	24.1 Arms	Rated Output:	4500 W
Rated Revolution Speed:	2000 rpm		21.5 N·m (219 kg·cm)	Torque Constant:	1.05 N·m/Arms (10.7 kg·cm/Arms)
Last Verified:	07/06/2025 12:18 PM	Rated Torque:			

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

