



## Sanyo Denki - R SANMOTION Servo Motors

### R2AA06020FXW80M



 **In Stock, Shipping Varies**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online  
Checkout



Free Ground  
Shipping



One Year  
Warranty

The **R2AA06020FXW80M** is a part of the **R SANMOTION Servo Motors Series** by **Sanyo Denki**.

## Specifications

**Armature Current At Stall:** 1.6 Arms

**Peak Torque At Stall:** 2.2 N·m

**Rated Output Power:** 0.2 kW

**Rated Torque:** 0.637 N·m

**Voltage Constant (per Phase):** 16.6 mV/min

**Continuous Torque At Stall:** 0.686 N·m

**Phase Resistance:** 2.7 ?

**Rated Power Rate:** 19 kW/s  
0.222 × 10??  
kg·m<sup>2</sup>

**Rotor Inertia:**

**Weight (we):** 0.96 kg

**Peak Armature Current At Stall:** 5.6 Arms


**Rated Armature Current:** 1.5 Arms

**Rated Speed:** 3000 min?<sup>1</sup>

**Torque Constant:** 0.476 N·m/Arms

**Last Verified:** 06/20/2025  
3:32 AM

## Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: [sales@automation-factory.com](mailto:sales@automation-factory.com)

## Shipping Options



## Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.