

Sanyo Denki - R SANMOTION Servo Motors

R2AAB8075FXSBLM



 **Request a Quote**

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **R2AAB8075FXSBLM** is a part of the **R SANMOTION Servo Motors Series** by **Sanyo Denki**.

Specifications

Brake Rated Current:	Approximately 0.07 A (DC90V) / 0.27 A (DC24V)	Continuous Torque At Stall:	Approximately 2.5 N·m	Flange Size:	80 mm square
Input Voltage:	AC200 V	Peak Armature Current:	Approximately 64 A	Peak Torque At Stall:	Approximately 8.4 N·m
Phase Resistance:	Approximately 3 ?	Rated Armature Current:	Approximately 18 A	Rated Output:	750 W
Rated Speed:	3000 min ⁻¹	Rated Torque:	Approximately 2.39 N·m	Torque Constant (kt):	Approximately 0.13 N·m/A
Voltage Constant (ke):	Approximately 4.5 mV/(min ⁻¹)	Last Verified:	06/20/2025 4:07 PM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.