



sales@automation-factory.com
1-919-443-0207

103H5333-0340



- ✔ Get a Quote in 5 minutes
- ✔ Parts ship in as little as 24 hours
- ✔ Up to half the cost of the manufacturer



One Year
Warranty

The **103H5333-0340** is a part of the **StepSyn Stepping Motors Series** by **Sanyo Denki**.

Specifications

Connector:	JST EHR-3	Driver Compatibility:	PMDSA1S3P01 and PMDSA1S3C01	Holding Torque:	0.196 Nm (27.75 oz-in)
Insulation Resistance:	Not less than 100M? at DC500V between winding and frame	Mass (weight):	0.3 kg (0.66 lbs)	Operating Current:	3A/phase (full step)
Rated Current:	3 A/phase	Rotor Inertia:	0.053x10^-4 kg·m² (0.29 oz·in²)	Step Angle:	1.2° per step
Terminal Type:	SEH-001T-P06	Voltage Supply:	DC24V	Winding Inductance:	0.5 mH/phase
Winding Resistance:	0.84 ?/phase	Withstand Voltage:	50/60 Hz, 500V AC between winding and frame for 1 minute	Last Verified:	06/05/2025 3:48 PM

Contact Us

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



© 2024 Automation Factory. All rights reserved.