



Vickers - EEA-PAM-5-A-33 Power Amplifiers

EEA-PAM-535-A-33



 In Stock, Ships 2-3 Days

- ☒ Get a Quote in 5 minutes
- ☒ Parts ship in as little as 24 hours
- ☒ Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **EEA-PAM-535-A-33** is a part of the **EEA-PAM-5-A-33 Power Amplifiers Series** by **Vickers**.

Specifications

Amplifier Shut-down Voltage:	<18V DC	Command Signal Input Impedance:	47k Ω (voltage), 100 Ω (current)	Command Signal Voltage Range:	$\pm 10V$
Edge Connectors:	DIN 41612 F48 male type	Electromagnetic Compatibility Directive:	CE - 2014/30/EU	Mass:	0.40 kg (0.88 lb) approx.
Output Voltage At Pin B2:	-10V $\pm 1\%$ x 5mA	Output Voltage At Pin Z2:	+10V $\pm 1\%$ x 5mA	Power Supply Nominal:	24V DC x 50W
Power Supply Range:	20 - 40V (including 10% max ripple)	Ramp Time Adjustment Range:	50 ms to 5s	Short Circuit Protection:	All outputs are short-circuit protected
Temperature Drift For Output Voltage:	<1mV/ $^{\circ}C$ through 0-50 $^{\circ}C$ range	Last Verified:	06/02/2025 3:24 AM		

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.