

Vickers - EEA-PAM Power Amplifiers

EEA-EDC-436-D1-32

 **In-Stock, Ships Fast**



- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **EEA-EDC-436-D1-32** is a part of the **EEA-PAM Power Amplifiers Series** by **Vickers**.

Specifications

Ambient Conditions - Operating: 0°C to +50°C

Ambient Conditions - Storage: -25°C to +85°C

Built-in Test Feature: Test modes for pump and loop configuration

Command Voltage Range: 0-10V or ±10V

Control Output Supplies: +15V, +10V x 5mA, -10V x 5mA

Current Range: 4-20mA or 0-20mA

Digital Outputs: Sensor failure, feedback match

Installation: DIN 41612 F48 connector with clear guidelines

Voltage Input Impedance: 10k Ω (sensor), 47k Ω (general inputs)

Weight: 0.4 kg (approx.)

Analog Outputs:

PID controller output, feedback signal, error signal
PID controller with user-configurable gains
Drive enable, ramp enable, integrator enable
20-40 V DC (including pk-to-pk ripple 10% max)

Control Features:

Digital Inputs:

Power Input Supply:

Last Verified:

03/10/2026
1:20 PM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods



Automation Factory sells factory new and pre-owned surplus products and maintains channels to procure supply. Automation Factory is not affiliated with nor an authorized distributor or representative of any manufacturers, brands or products listed. Designated trademarks, brand names, and brands appearing herein are the property of their respective owners.