

Vickers - EEA-PAM Power Amplifiers

**EEA-PAM-511-A-32-EN8**

 **In-Stock, Ships Fast**



- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- Up to half the cost of the manufacturer



Secure Online  
Checkout



Free Ground  
Shipping




One Year  
Warranty

The **EEA-PAM-511-A-32-EN8** is a part of the **EEA-PAM Power Amplifiers Series** by **Vickers**.

**Specifications**

<b>Adjustment:</b>	Front panel potentiometers for gain, ramp, and deadband	<b>Backplane Connector:</b>	DIN 41612 F48 (Male)		128.4 mm
<b>Card Height:</b>	175.24 mm	<b>Card Width:</b>	40.3 mm	<b>Card Depth:</b>	
<b>Connections:</b>	Plug-in terminal strip	<b>Connector Screw Size:</b>	M2.5 x 11	<b>Command Input Impedance:</b>	47 k $\Omega$
<b>Dimensions:</b>	100 x 160 mm (Eurocard)	<b>Eurocard Height:</b>	3U (IEC 297)	<b>Control Supply Output:</b>	$\pm 15$ V, 50 mA
<b>Input Signal Range:</b>	$\pm 10$ V analog (differential input)	<b>Mating Connector:</b>	DIN 41612 F48 (Female)	<b>Feedback:</b>	LVDT or feedback input supported
<b>Nominal Supply Voltage:</b>	24 VDC	<b>Operating Temperature Range:</b>	0°C to +50°C	<b>Mounting:</b>	Eurocard, Plug-in
<b>Power Consumption:</b>	Max. 15 W	<b>Power Supply Voltage:</b>	24 VDC	<b>Output Signal:</b>	Current output for proportional valve control Short-circuit and overload protected
<b>Ramp Time:</b>	30 s	<b>Reference Output:</b>	$\pm 10$ V, 5 mA	<b>Protection:</b>	05/25/2026 7:25 PM

**Contact Us**

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: [sales@wakeindustrial.com](mailto:sales@wakeindustrial.com)

**Shipping Options**



**Payment Methods**

