

Vickers - EEA-PAM Power Amplifiers

EEA-PAM-525-A-33

 **In-Stock, Ships 3-5 Days**



- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- Up to half the cost of the manufacturer



Secure Online
Checkout



Free Ground
Shipping



One Year
Warranty

The **EEA-PAM-525-A-33** is a part of the **EEA-PAM Power Amplifiers Series** by **Vickers**.

Specifications

Command Signal Monitor:	0-10V	Current Input Range:	~20mA	Disabled Voltage For Drive:	Open circuit or ?
Edge Connectors:	DIN 41612 F48	Enable Voltage For Drive:	9.8 - 40V	Input Impedance (current):	100?
Input Impedance (voltage):	47 k?	Overload Protection:	Automatic reset	Ramp Time Adjustment:	50 ms to 5s
Short Circuit Protection:	All outputs	Supply Voltage:	24V DC	Temperature Drift:	<1mV/C
Voltage Inputs:	~10V	Weight:	0.33 kg (0.15 lb)	Last Verified:	03/11/2026 3:10 AM

Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA

 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: sales@automation-factory.com

Shipping Options



Payment Methods

