

## Vickers - EEA-PAM Power Amplifiers

# EEA-PAM-533-E-32

 **Call For Quote**



- Get a Quote in 5 minutes
- Parts ship in as little as 24 hours
- Up to half the cost of the manufacturer



Secure Online  
Checkout



Free Ground  
Shipping





One Year  
Warranty

The **EEA-PAM-533-E-32** is a part of the **EEA-PAM Power Amplifiers Series** by **Vickers**.

## Specifications

<b>Alarm Output Current Max:</b>	50 mA	<b>Amplifier Shut-down Threshold:</b>	<18 VDC	<b>Connection Type:</b>	32-pin DIN 41612 connector
<b>Control Output:</b>	Proportional, for axial piston amplifier	<b>Control Output Voltage (lvdt):</b>	+15 V	<b>Current Consumption:</b>	max. 1.5 A
<b>Depth:</b>	175.24 mm	<b>Dimensions:</b>	100 mm x 160 mm (Eurocard)	<b>Din 41612 Connector Type:</b>	F48 Male
<b>Emc/ce Compliance:</b>	Yes	<b>Fuse Rating:</b>	2.5 A	<b>Height:</b>	128.4 mm
<b>Input Voltage:</b>	24 VDC	<b>Max Operating Temperature:</b>	50 °C	<b>Max Storage Temperature:</b>	85 °C
<b>Maximum Voltage:</b>	40V (including peak-to-peak ripple of ~10%)	<b>Min Operating Temperature:</b>	0 °C	<b>Minimum Voltage:</b>	20V
<b>Monitor Point Output Resistance:</b>	10 k?	<b>Mounting Type:</b>	Plug-in (Eurocard format)	<b>Nominal Supply Voltage:</b>	24 VDC
<b>Nominal Voltage:</b>	24V DC (~10% tolerance)	<b>Out-of-range Output Current Max:</b>	100 mA	<b>Power Consumption:</b>	50W
<b>Protection Class:</b>	IP20	<b>Sensor Current Input Max:</b>	20 mA	<b>Sensor Current Input Resistance:</b>	100 ?
<b>Sensor Voltage Input Max:</b>	24 V	<b>Signal Input:</b>	Voltage, or current (user configurable)	<b>Power Requirement:</b>	50 W
<b>Weight:</b>	Approx. 400 g	<b>Last Verified:</b>	05/11/2017		

## Contact Us

 1620 Old Apex Road, Cary, NC 27513, USA  
**Weight:** Approx. 400 g  
 Toll Free: [1-888-551-3082](tel:1-888-551-3082)

 International: [1-919-443-0207](tel:1-919-443-0207)

 Fax: [1-919-867-6204](tel:1-919-867-6204)

 Email: [sales@wakeindustrial.com](mailto:sales@wakeindustrial.com)

## Shipping Options



## Payment Methods

